

EDA5000E

EDA5000E



Brushless generator
Maintenance free.



Oil warning system
Engine stops automatically when oil level (pressure) has fallen below the prescribed level.



Non-fuse breaker
Easier 'on' & 'off' of AC output with circuit breaker.



Auto decompressor
Light recoil starting.



DC output capability
Convenient for battery charging.



Fuel gauge
Fuel level confirmation at a glance.



Voltmeter
Voltage confirmation at a glance.



Electric starter
Easier starting.



Frame
Easy to carry & solid protection.

On all models

On some models

Specification Sheet

Generator	
Type	Brushless AC Generator Single Phase
Rated voltage (V)	220
Frequency (Hz)	50
Rated output (kVA)	4.3
Max output (kVA)	4.8
DC output	12V / 8.3A terminal
Engine	
Type	4-stroke air cooled Diesel Engine
Starting system	Recoil / Electric
General	
L*W*H (mm)	673*500*542
Dry Weight (kg)	99.0
Fuel tank capacity(full)(l)	16.0
Operating hours (Hr)	9.4
Noise Level (db A)(7m)	76.0

Features	
Brushless	○
Voltage regulator	Condenser
Dual voltage	×
AC : Circuit breaker system	N.F.B
DC : Circuit breaker system	FUSE(10A)
Fuel level gauge	○
Oil warning system	○
Water temp.warning system	×
Charging warning system	×
Glow lamp	×
Voltage meter	○
Pilot lamp	×
Economy idle system	×
Acces.	
Transportation Kit	Option : 4 wheels
Remote starter kit	×
AC Plug	○
Fuse	10A*2

Receptacle

(15A+15A) 250V
20A250V