







ET-1

ET-1



-  **2-stroke reed valve engine**
Compact size & simple mechanism.
 -  **Brushless generator**
Maintenance free.
 -  **Circuit breaker(s)**
Fuseless type to protect the circuit against overcurrent.
 -  **DC output capability**
Convenient for battery charging.
 -  **Carrying Handle**
Easy to carry.
- On all models
 On some models

Specification Sheet

Generator		General	
Type	Brushless, Condenser Compensation, Synchronous AC Generator / Single Phase	L*W*H (mm)	367*312*375
Rated voltage (V)	230	Dry Weight (kg)	19.0
Frequency (Hz)	50	Fuel tank capacity(full)(l)	4.0
Rated output (kVA)	0.65	Operating hours (Hr)	6.0
Max Output (kVA)	0.78	Noise Level (db A)(7m)	56.0
DC output	12V/8.0A	Features	
Engine		Brushless	○
Type	2-stroke reed valve forced air-cooled	Voltage regulator	Condenser
Displacement	63cm ³	Circuit breaker system	Protector
Starting system	Recoil	Acces.	
		AC Plug	○
		DC charging cord	○
		Receptacle	
		 10 A 250V	

Please read your owner's manual and all labels before operation.